

Surface Mount Bandpass Filter

BPF-C4R5+

50Ω 2 to 7 MHz



Generic photo used for illustration purposes only
CASE STYLE: HU1186

The Big Deal

- Low insertion loss
- Good VSWR
- Miniature shielded package

Product Overview

BPF-C4R5+ is a bandpass filter fabricated using SMT technology. This filter offers good rejection and low insertion loss for use in aviation and communication systems. This unit uses a miniature high Q capacitors and wire welded inductors for high reliability.

Key Features

Feature	Advantages
Low insertion loss	Suitable for high performance applications.
Good VSWR, 1.1:1 typical in passband	The BPF-C4R5+ has very good VSWR which provides good matching when used with other devices.
Shielded package	Reduced interference with the surrounding components.

Notes

- A. Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.
B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.
C. The parts covered by this specification document are subject to Mini-Circuits standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms.jsp



Surface Mount Bandpass Filter

BPF-C4R5+

50Ω 2 to 7 MHz



Generic photo used for illustration purposes only
CASE STYLE: HU1186

Features

- Low insertion loss
- Good VSWR
- Miniature shielded package

Applications

- Aviation
- Communication systems

Electrical Specifications at 25°C


Parameter	F#	Frequency (MHz)	Min.	Typ.	Max.	Unit
Pass Band	Center Frequency	—	—	4.5	-	MHz
	Insertion Loss	F1-F2	2-7	0.5	1.5	dB
	VSWR	F1-F2	2-7	1.1	1.5	:1
Stop Band, Lower	Insertion Loss	DC-F3	DC-0.6	20	35.9	dB
	VSWR	DC-F3	DC-0.6	-	20	:1
Stop Band, Upper	Insertion Loss	F4-F5	17-2100	20	28.9	dB
	VSWR	F4-F5	17-2100	-	20	:1

Maximum Ratings


Operating Temperature	-40°C to 85°C
Storage Temperature	-55°C to 100°C
RF Power Input	1 W max.

Permanent damage may occur if any of these limits are exceeded.

Functional Schematic



Typical Frequency Response







Typical Performance Data at 25°C

Frequency (MHz)	Insertion Loss (dB)	VSWR (:1)	Frequency (MHz)	Group Delay (nsec)
0.10	88.93	898.07	2.0	250.52
0.60	35.20	293.81	2.2	212.56
0.66	30.30	215.92	2.6	165.56
0.79	20.51	92.29	2.8	150.39
1.08	3.05	4.05	3.0	132.37
1.10	2.43	3.31	3.2	127.88
2.00	0.25	1.06	3.4	123.03
4.50	0.29	1.09	3.6	117.89
7.00	0.49	1.04	3.8	112.44
9.00	1.00	1.34	4.0	107.33
9.90	2.17	2.34	4.2	103.11
10.30	3.21	3.22	4.4	99.60
14.20	20.03	20.48	4.8	94.30
17.00	29.73	25.63	5.0	92.33
17.10	30.03	25.75	5.4	89.40
500.00	99.85	43.88	5.8	87.64
950.00	78.75	35.82	6.2	86.75
1500.00	44.47	12.10	6.6	86.61
1960.00	38.39	2.77	6.8	86.83
2100.00	40.73	2.18	7.0	87.26

+RoHS Compliant

The +Suffix identifies RoHS Compliance. See our web site for RoHS Compliance methodologies and qualifications



Notes


- Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.
- Electrical specifications and performance data contained in this specification document are based on Mini-Circuits' applicable established test performance criteria and measurement instructions.
- The parts covered by this specification document are subject to Mini-Circuits standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms.jsp



Pad Connections

INPUT	2
OUTPUT	9
NOT CONNECTED	6 & 13
GROUND	1,3,4,5,7,8,10,11,12,14

Demo Board MCL P/N: TB-500+
Suggested PCB Layout (PL-294)




NOTES:

- TRACE WIDTH IS SHOWN FOR ROGERS R04350B,
 DIELECTRIC THICKNESS: .030" ± .002";
 COPPER: 1/2 OZ ON EACH SIDE.
 FOR OTHER MATERIALS TRACE WIDTH MAY NEED TO BE MODIFIED.
- BOTTOM SIDE OF THE PCB IS CONTINUOUS GROUND PLANE.

- DENOTES PCB COPPER LAYOUT WITH SMOBC (SOLDER MASK OVER BARE COPPER)
- DENOTES COPPER LAND PATTERN FREE OF SOLDERMASK

Outline Drawing




Outline Dimensions (inch / mm)

A	B	C	D	E	F	G	H
.870	.800	.25	.100	.097	--	.060	.040
22.10	20.32	6.35	2.54	2.46	--	1.52	1.02
J	K	L	M	N	P	wt	
.105	.910	--	.060	.060	--	grams	
2.67	23.11	--	1.52	1.52	--	2.85	

Note: Please refer to case style drawing for details

PCB Land Pattern



Suggested Layout,
 Tolerance to be within ±.002

Notes

- A. Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.
- B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.
- C. The parts covered by this specification document are subject to Mini-Circuits standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms.jsp