

75 Ω 5 to 120 MHz

The Big Deal

- Supports DOCSIS® 3.1 upstream bandwidth
- Low insertion loss, 0.2 dB
- Good return loss, 28 dB
- Low amplitude / phase unbalance, 0.2 dB / 2°
- Small size, 0.15 x 0.15 x 0.16"



CASE STYLE: AT1521

Product Overview

TC1-1T-75X+ is a 75Ω surface-mount, DC-isolated transformer with a secondary center tap, covering the 5 to 120 MHz band, supporting upstream bandwidth requirements for DOCSIS 3.1 systems and equipment. This model provides a 1:1 secondary/primary impedance ratio and is capable of handling up to 0.25W RF input power. It provides 0.2 dB insertion loss, 28 dB return loss, 0.2 dB amplitude unbalance and 2° phase unbalance. Featuring core and wire construction mounted on a 5-lead plastic base with tin over nickel termination finish, the unit measures 0.15 x 0.15 x 0.16" to accommodate dense circuit board layouts. It also incorporates Mini-Circuits' Top Hat® feature for faster, more accurate pick-and-place assembly.

Key Features

Feature	Advantages
Supports DOCSIS 3.1 upstream bandwidth requirements	This model is optimized for use over the upstream bandwidth for CATV and broadband fiber networks including DOCSIS 3.1 systems.
Low insertion loss, 0.2 dB	Provides excellent transmission of signal power from input to output.
Good return loss, 28 dB	Provides excellent matching for 75Ω systems.
Low unbalance: - 0.2dB amplitude unbalance - 2° phase unbalance	Low unbalance improves a system's electromagnetic compatibility by rejecting unwanted common-mode noise.
DC isolation	Provides DC isolation between circuits and efficient AC transmission, eliminating the need for external DC biasing components.
Secondary center tap	Allows DC feed up to 30 mA and DC bias without adding bias tees into the signal chain.
Small footprint (0.15 x 0.15 x 0.16")	Accommodates tight space requirements for dense PCB layouts.
Top Hat® feature	Improves speed and accuracy of pick and place assembly and provides clear device marking for visual inspection.



TC1-1T-75X+

75Ω 5 to 120 MHz

Features

- DOCSIS 3.1 suitable
- · plastic base with leads
- aqueous washable

Applications

- impedance matching
- unbalance to balance transformation
- cable/CATV and broadband fiber networks



Generic photo used for illustration purposes only

CASE STYLE: AT1521

+ROHS Compliant
The +Suffix identifies RoHS Compliance. See our web site for RoHS Compliance methodologies and qualifications



Electrical Specifications at 25°C

Parameter	Frequency (MHz)	Min.	Тур.	Max.	Unit
Impedance Ratio			1		Ohm
Frequency Range		5	_	120	MHz
Insertion Loss*	5 - 75	_	0.1	0.4	dB
insertion Loss*	75 - 120	_	0.3	0.6	
Amplitude Unbalance	5 - 75	_	0.1	0.2	dB
Ampilitude Oribalance	75 - 120	_	0.2	0.3	
Phase Unbalance	5 - 75	_	1	4	Degree
Priase difibalance	75 - 120	_	3	6	
	5 - 20	25	30	_	
Return Loss	20-75	23	28	_	dB
	75-120	20	25	_	

 $^{^{\}star} \text{Insertion Loss}$ is referenced to mid-band loss, 0.25 dB typ.

Maximum Ratings

Parameter	Ratings		
Operating Temperature	-40°C to 85°C		
Storage Temperature	-55°C to 100°C		
RF Power	0.25W		
DC Current	30mA		

Permanent damage may occur if any of these limits are exceeded.


Pin Connections


Function	Pin Number				
PRIMARY DOT	6				
PRIMARY	4				
SECONDARY DOT	1				
SECONDARY	3				
SECONDARY CT	2				

Product Marking



Config. A





Outline Dimensions (inch)

F	Е	D	С	В	Α
.025	.040	.050	.160	.150	.150
0.64	1.02	1.27	4.06	3.81	3.81
wt		K	J	Н	G
grams		.030	.190	.065	.028
0.15		0.76	4.83	1.65	0.71

Typical Performance Data

FREQUENCY (MHz)	INSERTION LOSS (dB)	INPUT R. LOSS (dB)	AMPLITUDE UNBALANCE (dB)	PHASE UNBALANCE (Deg.)
5.00	0.26	30.33	0.01	0.20
10.00	0.25	32.29	0.00	0.32
20.00	0.26	32.98	0.00	0.55
50.00	0.31	31.47	0.01	1.18
70.00	0.33	29.95	0.00	1.59
80.00	0.34	29.15	0.00	1.81
90.00	0.35	28.34	0.01	2.03
100.00	0.36	27.58	0.02	2.25
110.00	0.37	26.88	0.02	2.46
120.00	0.38	26.26	0.03	2.68

