# Coaxial **High Pass Filter**

### 50Ω

# 1400 to 5000 MHz

#### **Maximum Ratings**

Operating Temperature	-55°C to 100°C
Storage Temperature	-55°C to 100°C
RF Power Input*	7W max. at 25°C

\* Passband rating, derate linearly to 3W at 100°C ambient. Permanent damage may occur if any of these limits are exceeded.

#### **Features**

- rugged unibody construction, small size
- 7 sections
- temperature stable
- excellent power handling, 7W
- · low cost

#### Applications

- sub-harmonic rejection
- transmitters/receivers
- lab use



Generic photo used for illustration purposes only

CASE STYLE: FF704

Connectors Model SMA VHF-1300+

+RoHS Compliant The +Suffix identifies RoHS Compliance. See our web site for RoHS Compliance methodologies and qualifications

## **Outline Drawing**



#### Outline Dimensions (inch)

В	D	Е	wt
.410	1.43	.312	grams
10.41	36.32	7.92	10.0

Electrical Specifications (T<sub>AMB</sub>=25°C) STOP BAND fco, MHz PASSBAND (MHz) **VSWR** (:1) NO. OF (MHz) SECTIONS Nom. Тур. Min Frequency (MHz) (loss 3 dB) (loss < 1.3 dB) (loss < 2 dB)(loss > 40 dB)(loss > 20 dB)Тур. Max Тур. Stopband 1.5:1 1400-5000 1400-4000 680 930 1300 1510-4000 20:1 7

#### typical frequency response

#### 40dB **ATTENUATION** 20dB 3dB Fco F 1.3dB FREQUENCY

### electrical schematic



#### Typical Darformanaa Data

Frequency (MHz)	Insertion Loss (dB)	VSWR (:1)
1	89.20	868.59
100	73.46	868.59
680	45.52	78.97
930	27.34	39.49
1130	13.31	17.05
1230	6.74	6.91
1300	3.40	3.29
1400	1.42	1.58
1510	1.01	1.36
2000	0.64	1.31
2500	0.59	1.47
3000	0.43	1.29
4000	0.49	1.42
5000	1.48	2.73
7000	4.52	7.47



Notes

A Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document. B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions. C. The parts covered by this specification document are subject to Mini-Circuits standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuit's website at www.minicircuits.com/WCLStore/terms.jsp

### Mini-Circuits

REV. G M151107 VHF-1300 EDR-6437/6 RVN/AD/AM 200520 Page 1 of 1

www.minicircuits.com P.O. Box 350166, Brooklyn, NY 11235-0003 (718) 934-4500 sales@minicircuits.com