## Ultra-Small SPST Analog Switch

The NL7WB66 is a very low  $R_{ON}$  dual SPST analog switch.  $R_{ON}$  is 5.0  $\Omega$  (Typ) at 5.0 V. The device is offered in the very popular low cost US8 package. It is designed as a general purpose dual switch and can be used to switch either analog signals such as audio and video or digital signal such as TTL, CMOS, LVDS, ECL, or complex digital signals such as QPSK.

#### Features

- Excellent Performance  $RDS_{ON} = 5.0 \Omega$  at 5.0 V
- High Speed Operation:  $t_{PD} = 0.25$  ns (Max) at 5.0 V
- 1.65 to 5.5 V Operating Range
- Reduced Threshold Voltages for LVTTL on Control Pin
  - Eliminates the Need for Translators for Many Applications
  - TTL Compatibility when V<sub>CC</sub> is 5.0 V
  - Can Operate with 1.8 V Inputs, if V<sub>CC</sub> is 3.0
  - Also Meets Full CMOS Specifications
- Ultra–Low Charge Injection = 7.5 pC at 5.0 V
- Low Stand-by Power  $I_{CC} = 1.0$  nA (Max) at  $T_A = 25^{\circ}C$
- Control Pins IN1, IN2, are Overvoltage Tolerant
- Pin for Pin Replacement TC7WB66, NC7WB66, 74LVC2G66
- ESD Protection:
  - Machine Model >200 V,
  - Human Body Model >2000 V
- Latchup Max Rating: 200 mA
- These Devices are Pb–Free, Halogen Free/BFR Free and are RoHS Compliant

#### **Typical Applications**

- Cell Phones
- PDAs
- Digital Still Cameras
- Video
- Digital Video



Figure 1. Pin Assignment Diagram



## **ON Semiconductor®**

www.onsemi.com

#### MARKING DIAGRAM



AJ = Device Code M = Date Code\*

= Pb–Free Package

(Note: Microdot may be in either location) \*Date Code orientation may vary depending upon manufacturing location.

#### PIN ASSIGNMENT

Pin	Function	οντ
1	NO1	-
2	COM1	-
3	OE2	Yes
4	GND	-
5	NO2	-
6	COM2	-
7	OE1	Yes
8	V <sub>CC</sub>	-

#### FUNCTION TABLE

On/Off Enable Input	State of Analog Switch
L	Off
н	On

#### **ORDERING INFORMATION**

See detailed ordering and shipping information in the package dimensions section on page 5 of this data sheet.

#### MAXIMUM RATINGS

Symbol	Rating		Value	Unit
V <sub>CC</sub>	DC Supply Voltage		-0.5 to +7.0	V
VI	DC Input Voltage		-0.5 to +7.0	V
Vo	DC Output Voltage		-0.5 to +7.0	V
I <sub>IK</sub>	DC Input Diode Current	-50	mA	
Ι <sub>ΟΚ</sub>	DC Output Diode Current	V <sub>O</sub> < GND	-50	mA
Ι <sub>Ο</sub>	DC Output Sink Current		±50	mA
I <sub>CC</sub>	DC Supply Current per Supply Pin	±100	mA	
I <sub>GND</sub>	DC Ground Current per Ground Pin		±100	mA
T <sub>STG</sub>	Storage Temperature Range		-65 to +150	°C
ΤL	Lead Temperature, 1 mm from Case for 10 Seconds		260	°C
Τ <sub>J</sub>	Junction Temperature under Bias		+ 150	°C
$\theta_{JA}$	Thermal Resistance		250	°C/W
PD	Power Dissipation in Still Air at 85°C		250	mW
MSL	Moisture Sensitivity		Level 1	-
F <sub>R</sub>	Flammability Rating	Oxygen Index: 28 to 34	UL 94 V–0 @ 0.125 in	-
V <sub>ESD</sub>	, , , , , , , , , , , , , , , , , , ,	Human Body Model (Note 2) Machine Model (Note 3) arged Device Model (Note 4)	> 2000 > 200 N/A	V

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected. 1. Measured with minimum pad spacing on an FR4 board, using 10 mm-by-1 inch, 2-ounce copper trace with no air flow.

2. Tested to EIA/JESD22-A114-A.

3. Tested to EIA/JESD22-A115-A.

4. Tested to JESD22-C101-A.

#### **RECOMMENDED OPERATING CONDITIONS**

Symbol	bol Characteristics			Max	Unit
V <sub>CC</sub>	Positive DC Supply Voltage			5.5	V
V <sub>IN</sub>	Digital Input Voltage (Enable)			5.5	V
V <sub>IO</sub>	Static or Dynamic Voltage Across an Off Switch			V <sub>CC</sub>	V
V <sub>IS</sub>	Analog Input Voltage NO COM			V <sub>CC</sub>	V
T <sub>A</sub>	Operating Temperature Range, All Package Types			+125	°C
t <sub>r</sub> , t <sub>f</sub>	Input Rise or Fall Time (Enable Input)	$V_{CC} = 3.3 V \pm 0.3 V$ $V_{CC} = 5.0 V \pm 0.5 V$	0 0	100 20	ns/V

Functional operation above the stresses listed in the Recommended Operating Ranges is not implied. Extended exposure to stresses beyond the Recommended Operating Ranges limits may affect device reliability.

#### **DEVICE JUNCTION TEMPERATURE VS. TIME TO** 0.1% BOND FAILURES

Junction Temperature °C	Time, Hours	Time, Years
80	1,032,200	117.8
90	419,300	47.9
100	178,700	20.4
110	79,600	9.4
120	37,000	4.2
130	17,800	2.0
140	8,900	1.0





DC CHARACTERISTICS – Digital Section (Voltage	ges Referenced to GND)
---	------------------------

				Guara	anteed Max L	imit	
Symbol	Parameter	Condition	v <sub>cc</sub>	25°C	-40 to 85°C	–55 to <125°C	Unit
V <sub>IH</sub>	High-level Input Voltage, Control Input		1.65 to 1.95 2.3 to 2.7 3.0 to 3.6 4.5 to 5.5	V <sub>CC</sub> x 0.65 V <sub>CC</sub> x 0.7 V <sub>CC</sub> x 0.7 V <sub>CC</sub> x 0.7	V <sub>CC</sub> x 0.65 V <sub>CC</sub> x 0.7 V <sub>CC</sub> x 0.7 V <sub>CC</sub> x 0.7	V <sub>CC</sub> x 0.65 V <sub>CC</sub> x 0.7 V <sub>CC</sub> x 0.7 V <sub>CC</sub> x 0.7	V
V <sub>IL</sub>	Low–level Input Voltage, Control Input		1.65 to 1.95 2.3 to 2.7 3.0 to 3.6 4.5 to 5.5	V <sub>CC</sub> x 0.35 V <sub>CC</sub> x 0.3 V <sub>CC</sub> x 0.3 V <sub>CC</sub> x 0.3	V <sub>CC</sub> x 0.35 V <sub>CC</sub> x 0.3 V <sub>CC</sub> x 0.3 V <sub>CC</sub> x 0.3	V <sub>CC</sub> x 0.35 V <sub>CC</sub> x 0.3 V <sub>CC</sub> x 0.3 V <sub>CC</sub> x 0.3	V
I <sub>IN</sub>	Maximum Input Leakage Current, Enable Inputs	$V_{IN} = 5.5 V \text{ or GND}$	0 V to 5.5 V	<u>+</u> 0.1	<u>+</u> 1.0	<u>+</u> 1.0	μΑ
I <sub>CC</sub>	Maximum Quiescent Supply Current (per package)	Enable and VIS = VCC or GND	5.5	1.0	1.0	2.0	μΑ

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.

						Guaranteed Ma	ax Limit	
Symbol	Parameter	Conditio	on	V <sub>CC</sub>	25°C	–40 to 85°C	–55 to <125°C	Unit
R <sub>ON</sub>	On–State Switch Resistance	$\begin{array}{l} V_{IS} = V_{CC} \\ V_{IS} = GND \\ V_{IS} = GND \\ V_{IS} = GND \\ V_{IS} = V_{CC} \\ V_{IS} = GND \\ V_{IS} = V_{CC} \\ V_{IS} = 2.4 \\ V_{IS} = GND \end{array}$	$I_{S} = 4 \text{ mA}$ $I_{S} = 4 \text{ mA}$ $I_{S} = 8 \text{ mA}$ $I_{S} = 8 \text{ mA}$ $I_{S} = 24 \text{ mA}$ $I_{S} = 24 \text{ mA}$ $I_{S} = 32 \text{ mA}$ $I_{S} = 15 \text{ mA}$ $I_{S} = 32 \text{ mA}$	1.65 1.65 2.3 2.3 3.0 3.0 4.5 4.5 4.5	30 15 20 10 15 7.0 10 8.0 5.0	30 15 20 10 15 7.0 10 8.0 5.0	30 15 20 10 15 7.0 10 8.0 5.0	Ω
R <sub>ON(p)</sub>	Peak On–State Resistance		$I_S = 4 \text{ mA}$ $I_S = 8 \text{ mA}$ $I_S = 24 \text{ mA}$ $I_S = 32 \text{ mA}$	1.65 2.3 3.0 4.5	120 30 20 15	120 30 20 15	120 30 20 15	Ω
$\Delta R_{ON}$	Difference of On–State Resistance between Switches	$V_{IS} = V_{CC}$ to GND, $V_{IN} = V_{IH}$	$I_S = 4 \text{ mA}$ $I_S = 8 \text{ mA}$ $I_S = 24 \text{ mA}$ $I_S = 32 \text{ mA}$	1.65 2.3 3.0 4.5	1.2 1.3 1.5 2.0	1.2 1.3 1.5 2.0	1.2 1.3 1.5 2.0	Ω
R <sub>FLAT</sub>		$V_{IS} = V_{CC}$ to GND	$I_{S} = 4 \text{ mA}$ $I_{S} = 8 \text{ mA}$ $I_{S} = 24 \text{ mA}$ $I_{S} = 32 \text{ mA}$	1.65 2.3 3.0 4.5	240 60 14 5.0	240 60 14 5.0	240 60 14 5.0	Ω
I <sub>NO(OFF)</sub>	Off Leakage Current	$V_{IN} = V_{IL}$ $V_{NO} = 1.0 \text{ V}, V_{COM}$ $V_{COM} = 1.0 \text{ V} \text{ and } V$		5.5	1.0	10	100	nA
I <sub>COM(OFF)</sub>	Off Leakage Current	V <sub>IN</sub> = V <sub>IL</sub> V <sub>NO</sub> = 4.5 V or 1.0 V <sub>COM</sub> = 1.0 V or 4.9	V 5 V	5.5	1.0	10	100	nA

#### DC ELECTRICAL CHARACTERISTICS – Analog Section

### **AC ELECTRICAL CHARACTERISTICS** (Input $t_r = t_f = 3.0$ ns)

					Gu	aranteed	d Max Li	mit			
			V <sub>CC</sub> = ±0.	: 1.8 V 15 V	V <sub>CC</sub> = ±0	2.5 V .2 V	V <sub>CC</sub> = ±0	3.3 V .3 V	V <sub>CC</sub> = ±0	5.0 V .5 V	
Symbol	Parameter	Test Conditions	Min	Max	Min	Max	Min	Max	Min	Max	Unit
t <sub>ON</sub>	Output Enable Time		2.3	10	1.6	5.6	1.5	4.4	1.3	3.9	ns
t <sub>OFF</sub>	Output Disable Time		2.5	10.5	1.2	6.9	2.0	7.2	1.1	6.3	ns
t <sub>PD</sub>	Propagation Delay Time		-	0.55	-	0.5	-	0.35	-	0.25	ns

		Typical @ 25°C, V <sub>CC</sub> = 5.0 V	Unit
C <sub>IN</sub>	Maximum Input Capacitance, Select Input	3.0	рF
C <sub>NO1</sub> or C <sub>NO2</sub>	Analog I/O (Switch Off)	10	
C <sub>COM(OFF)</sub>	Common I/O (Switch Off)	10	
C <sub>COM(ON)</sub>	Feed-through (Switch Off)	10	

#### ADDITIONAL APPLICATIONS CHARACTERISTICS (Voltage Reference to GND Unless Noted)

Symbol	Parameter	Condition	V <sub>CC</sub> (V)	Typical 25°C	Unit
BW	Maximum On–Channel –3.0 dB Bandwidth or Minimum Frequency Response	$V_{IS}$ = 0 dBm $V_{IS}$ centered between $V_{CC}$ and GND	2.0 3.0 4.5	102 180 186	MHz
V <sub>ONL</sub>	Maximum Feed-Through On Loss	$V_{IS}$ = 0 dBm @ 10 kHz $V_{IS}$ centered between $V_{CC}$ and GND	2.0 3.0 4.5	-2.2 -0.8 -0.4	dB
V <sub>ISO</sub>	Off-Channel Isolation	$f = 100 \text{ kHz}$ $V_{IS} = 1.0 \text{ V RMS}$ $V_{IS} \text{ centered between } V_{CC} \text{ and GND}$	2.0 3.0 4.5	-73 -74 -75	dB
Q	Charge Injection Enable Input to Common I/O	$\label{eq:VIS} \begin{array}{l} V_{IS} = V_{CC} \text{ to GND, } F_{IS} \ = 20 \text{ kHz} \\ t_{r} = t_{f} = 3.0 \text{ nS} \\ R_{IS} = 0 \ \Omega, \ C_{L} = 100 \text{ pF} \end{array}$	3.0 5.5	4.8 7.5	рС
THD	Total Harmonic Distortion TDH + Noise	$\label{eq:FIS} \begin{array}{l} F_{IS} = 10 \text{ Hz to } 100 \text{ kHz}, \\ R_L = R_{gen} = 600 \ \Omega, \ C_L = 50 \text{ pF} \\ V_{IS} = 3.0 \ V_{PP} \text{ Sine Wave} \\ V_{IS} = 5.0 \ V_{PP} \text{ Sine Wave} \end{array}$	3.0 5.5	0.19 0.06	%

#### **DEVICE ORDERING INFORMATION**

Device Order Number	Package	Shipping <sup>†</sup>
NL7WB66USG	US8 (Pb–Free)	3000 Units / Tape & Reel

+For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.

### TIMING INFORMATION



DATE 30 APR 2021





SCALE 4 :1

SEATING PLANE

μD



С

0.10 (0.004) T

NOTES

US8 CASE 493 ISSUE E

н

DETAIL E

- 1. DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982.
- 2. CONTROLLING DIMENSION: MILLIMETERS

0.10 TYP

- 3. DIMENSION A DOES NOT INCLUDE MOLD FLASH, PROTRUSION, OR GATE BURR. MOLD FLASH, PROTRUSION, OR GATE BURR SHALL NOT EXCEED 0.14 (0.0055') PER SIDE.
- 4. DIMENSION B DOES NOT INCLUDE INTERLEAD FLASH OR PROTRUSION. INTERLEAD FLASH AND PROTRUSION SHALL NOT EXCEED 0.14 (0.0055') PER SIDE.
- LEAD FINISH IS SOLDER PLATING WITH THICKNESS OF 0.0076-0.0203 MM (0.003-0.008\*).
- 6. ALL TOLERANCE UNLESS OTHERWISE SPECIFIED ±0.0508 MM (0.002").

	MILLIMETERS		INCHES	
DIM	MIN.	MAX.	MIN.	MAX.
A	1.90	2.10	0.075	0.083
В	2.20	2.40	0.087	0.094
С	0.60	0.90	0.024	0.035
D	0.17	0.25	0.007	0.010
F	0.20	0.35	0.008	0.014
G	0.50 BSC		0.020 BSC	
н	0.40 REF		0.016 REF	
J	0.10	0.18	0.004	0.007
к	0.00	0.10	0.000	0.004
L	3.00	3.25	0.118	0.128
м	0*	6*	0*	6*
N	0*	10*	0*	10*
Р	0.23	0.34	0.010	0.013
R	0.23	0.33	0.009	0.013
S	0.37	0.47	0.015	0.019
U	0.60	0.80	0.024	0.031
V	0.12 BSC		0.005 BSC	

#### GENERIC MARKING DIAGRAM\*



(Note: Microdot may be in either location)

\*This information is generic. Please refer to device data sheet for actual part marking. Pb–Free indicator, "G" or microdot "●", may or may not be present. Some products may not follow the Generic Marking.

DOCUMENT NUMBER:	98AON04475D	Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red.			
DESCRIPTION:	US8		PAGE 1 OF 1		
ON Semiconductor and ()) are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. ON Semiconductor does not convey any license under its patent rights nor the rights of others.					

Bx 0.46

0.20

**⊕**0.10 (0.004) **₩**TXY

MOUNTING FOOTPRINT

ON Semiconductor and are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at <u>www.onsemi.com/site/pdf/Patent-Marking.pdf</u>. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor date sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use a a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor houteds for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officers, employees, subsidiaries

#### PUBLICATION ORDERING INFORMATION

#### LITERATURE FULFILLMENT:

#### TECHNICAL SUPPORT

ON Semiconductor Website: www.onsemi.com

Email Requests to: orderlit@onsemi.com

North American Technical Support: Voice Mail: 1 800–282–9855 Toll Free USA/Canada Phone: 011 421 33 790 2910 Europe, Middle East and Africa Technical Support: Phone: 00421 33 790 2910 For additional information, please contact your local Sales Representative