

IGBT

FGS15N40L

General Description

Insulated Gate Bipolar Transistors(IGBTs) with trench gate structure have superior performance in conductance and switching to planar gate structure and also have wide noise immunity. These devices are well suitable for strobe application

Features

- High Input Impedance
- High Peak Current Capability (130A)
- Easy Gate Drive

Application

Strobe Flash





Absolute Maximum Ratings

T_C = 25°C unless otherrwise noted

Symbol	Description	FGS15N40L	Units
V _{CES}	Collector-Emitter Voltage	400	V
V _{GES}	Gate-Emitter Voltage	± 6	V
I _{CM (1)}	Pulsed Collector Current	130	А
P _C	Maximum Power Dissipation @ $T_a = 25^{\circ}C$	2.0	W
TJ	Operating Junction Temperature	-40 to +150	°C
T _{stg}	Storage Temperature Range	-40 to +150	°C
TL	Maximum Lead Temp. for soldering PurPoses from case for 5 secnds	300	°C

Notes:
(1) Repetitive rating: Pulse width limited by max. junction temperature

Thermal Characteristics

Symbol	Parameter	Тур.	Max.	Units
$R_{\theta,JA}$	Thermal Resistance, Junction-to-Ambient(PCB Mount)		62.5	°C/W

Notes: Mounted on 1" square PCB(FR4 or G-10 Material)

Symbol	Parameter	Test Conditions	Min.	Тур.	Max.	Units
Off Cha	racteristics					
BV _{CES}			450			V
I _{CES}					10	μΑ
I _{GES}	G-E leakage Current	$V_{GE} = V_{GES}, V_{CE} = 0V$			± 0.1	μΑ
On Chai V _{GE(th)}	racteristics G-E threshold Voltage	$I_C = 0V$, $I_C = 1mA$		_	1.4	V
On Cha	racteristics					
V _{CE(sat)}	C-E Saturation Voltage	$I_C = 130A$, $V_{GE} = 4.0V$	2.0	4.5	8.0	V
Dynamic Characteristics Cies Input Capacitance						
C _{ies}	Input Capacitance	V _{GF} = 0V , V _{CF} = 30V		3800		pF
C _{ies}	Input Capacitance Output Capacitance	V _{GE} = 0V , V _{CE} = 30V f = 1MHz		45		pF
C _{ies}	Input Capacitance					
C _{ies} C _{oes} C _{res}	Input Capacitance Output Capacitance			45		pF
C _{ies} C _{oes} C _{res}	Input Capacitance Output Capacitance Reverse Transfer Capacitance	f = 1MHz		45		pF
C _{ies} C _{oes} C _{res} Switching	Input Capacitance Output Capacitance Reverse Transfer Capacitance ng Characteristics	f = 1MHz V _{CC} = 300V , I _C = 130A		45 30		pF pF
C _{ies} C _{oes} C _{res}	Input Capacitance Output Capacitance Reverse Transfer Capacitance ng Characteristics Turn-On Delay Time	f = 1MHz		45 30 0.15		pF pF

Notes : Recommendation of Rg Value : Rg $\geq 15 \Omega$




Fig 1. Typical Output Chacracteristics




Fig 2. Saturation Voltage vs. Case Temerature at Variant Current Level




Fig 3. Saturation Voltage vs. V_{GE}




Fig 4. Saturation Voltage vs. V_{GE}




Fig 5. Saturation Voltage vs. V_{GE}




Fig 6. Capacitance Characteristics

©2001 Fairchild Semiconductor Corporation





Fig 7. Collector Current Limit Vs Gate - Emitter Voltage Limit



TRADEMARKS

The following are registered and unregistered trademarks Fairchild Semiconductor owns or is authorized to use and is not intended to be an exhaustive list of all such trademarks.

$ACEx^{TM}$	FAST [®]	OPTOLOGIC™	SMART START™	VCX^{TM}
Bottomless™	FASTr™	OPTOPLANAR™	STAR*POWER™	
CoolFET™	FRFET™	PACMAN™	Stealth™	
$CROSSVOLT^{rM}$	GlobalOptoisolator™	POP™	SuperSOT™-3	
DenseTrench™	GTO™	Power247™	SuperSOT™-6	
DOME™	HiSeC™	PowerTrench [®]	SuperSOT™-8	
EcoSPARK™	ISOPLANAR™	QFET™	SyncFET™	
E ² CMOS™	LittleFET™	QS™	TruTranslation™	
EnSigna™	MicroFET™	QT Optoelectronics™	TinyLogic™	
FACT™	MicroPak™	Quiet Series™	UHC™	
FACT Quiet Series™	MICROWIRE™	SLIENT SWITCHER®	UltraFET [®]	

STAR*POWER is used under license

DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR INTERNATIONAL.

As used herein:

- 1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, or (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in significant injury to the user.
- 2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

PRODUCT STATUS DEFINITIONS

Definition of Terms

Datasheet Identification	Product Status	Definition
Advance Information	Formative or In Design	This datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	This datasheet contains preliminary data, and supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
No Identification Needed	Full Production	This datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
Obsolete	Not In Production	This datasheet contains specifications on a product that has been discontinued by Fairchild semiconductor. The datasheet is printed for reference information only.

©2001 Fairchild Semiconductor Corporation Rev. H4